



Terminal

Plug-screw terminal 3, 4pin
max. 2,5 qmm

- | | | |
|---|--------|-------------|
| 1 | L | Line |
| 2 | N | " |
| 3 | PE | " |
| 4 | output | 24V AC (G) |
| 5 | " | " |
| 6 | output | 24V AC (G0) |
| 7 | " | - |

LED 24V output

Fuse 24V output

Technical Data

| | |
|--------------------------|----------------------------|
| Line input, pin 1-3 | 230V AC, +-10% |
| Power current | max. 0,6 A, peak 3A |
| Frequency | 40-60 Hz |
| Output, pin 4/5 – 6/7 | 24V AC |
| Output current | max. 4A, |
| Indication | LED 24V output |
| Fuse F1, line (internal) | 1,6A T, TR5 miniature fuse |
| Fuse F2, output 24V | 5A, FK 1 (car fuse) |
| Standard specification | EN 60742, EN 61558 |
| Insulation in-out-case | 4 kV AC |
| Operating temperature | -10 - +50°C |
| Storage temperature | -30 - +80°C |
| Construction | Sheet-steel, TS35, EN50022 |
| Weight | 2400 g |
| Dimensions | 79 x 100 x 102mm (WxHxD) |

Power supply 24V AC. Transformer with primary and secondary fuse.

Robust designed for the use in industrial applications. Operating status shown by LED.

RINCK ELECTRONIC GMBH

Kleekamp 6
27356 Rotenburg Wümme
www.rinck-electronic.de
info@rinck-electronic.de

POWER SUPPLY TRAF0 230V.24V-4A

| | |
|------------|----------------|
| Input | 230 V AC Line |
| Output | 24V AC, max.4A |
| Indication | LED |

A 104

E_TRAFO100W 23.03.15