



TRAFO230V.24V-6,5A

## Terminal

Plug-screw terminal 3, 4pin  
max. 2,5 qmm

- |   |        |             |
|---|--------|-------------|
| 1 | L      | Line        |
| 2 | N      | "           |
| 3 | PE     | "           |
| 4 | output | 24V AC (G)  |
| 5 | "      | "           |
| 6 | output | 24V AC (G0) |
| 7 | "      | -           |

LED 24V output

Fuse 24V output

## Technical Data

|                          |                             |
|--------------------------|-----------------------------|
| Line input, pin 1-3      | 230V AC, +-10%              |
| Power current            | max. 0,8 A, peak 3A         |
| Frequency                | 40-60 Hz                    |
| Output, pin 4/5 – 6/7    | 24V AC                      |
| Output current           | max. 6,5A,                  |
| Indication               | LED 24V output              |
| Fuse F1, line (internal) | 3,15A T, TR5 miniature fuse |
| Fuse F2, output 24V      | 7,5A, FK 1 (car fuse)       |
| Standard specification   | EN 60742, EN 61558          |
| Insulation in-out-case   | 4 kV AC                     |
| Operating temperature    | -10 - +50°C                 |
| Storage temperature      | -30 - +80°C                 |
| Construction             | Sheet-steel, TS35, EN50022  |
| Weight                   | 2400 g                      |
| Dimensions               | 79 x 100 x 102mm (WxHxD)    |

Power supply 24V AC. Transformer with primary and secondary fuse.  
Robust designed for the use in industrial applications. Operating status shown by LED.

### **RINCK ELECTRONIC GMBH**

Kleekamp 6  
27356 Rotenburg Wümme  
[www.rinck-electronic.de](http://www.rinck-electronic.de)  
info@rinck-electronic.de

### **POWER SUPPLY TRAFO 230V.24V-6,5A**

|            |                  |
|------------|------------------|
| Input      | 230 V AC Line    |
| Output     | 24V AC, max.6,5A |
| Indication | LED              |

**A 105**

E\_TRAFO160W 23.03.15